

SHENZHEN TIBTRONIX TECHNOLOGY CO., LTD.

GQPLFG06D

40Gb/s IR4 2km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

2013/6/1



Shenzhen Tibtronix Technology Co., Ltd.

3/F, 12th Building, Nangang 1st Industrial Park, Baimang Xili, Songbai Road, Nanshan District, Shenzhen, China

Tel: +86 755 23316583

Fax: +86 755 29810056

E-mail: sales@tibtronix.com

<http://www.tibtronix.com>

Features:

- ✧ 4 independent full-duplex channels
- ✧ Up to 11.2Gbps per channel bandwidth
- ✧ Aggregate bandwidth of > 40Gbps
- ✧ Duplex LC connector
- ✧ QSFP MSA compliant
- ✧ Up to 2 km transmission Single Mode Fiber
- ✧ Uncooled 4x10Gb/s CWDM transmitter
- ✧ Single +3.3V power supply operating
- ✧ IEEE 802.3ba Electrical Interface
- ✧ Built-in digital diagnostic functions
- ✧ Temperature range 0°C to 70°C
- ✧ RoHS Compliant Part

Applications:

- ✧ Data centers Interconnect
- ✧ 40G Ethernet
- ✧ Switches and Routers
- ✧ Infiniband QDR/DDR

Description:

The GQPLFG06D is a transceiver module designed for 2Km optical communication applications. The design is compliant to 40GBASE-IR4 of the IEEE P802.3ba standard. The module converts 4 inputs channels (ch) of 10Gb/s electrical data to 4 CWDM optical signals, and multiplexes them into a single channel for 40Gb/s optical transmission. Reversely, on the receiver side, the module optically de-multiplexes a 40Gb/s input into 4 CWDM channels signals, and converts them to 4 channel output electrical data.

The central wavelengths of the 4 CWDM channels are 1271, 1291, 1311 and 1331 nm as members of the CWDM wavelength grid defined in ITU-T G694.2. It contains a duplex LC connector for the optical interface and a 38-pin connector for the electrical interface. To minimize the optical dispersion in the long-haul system, single-mode fiber (SMF) has to be applied in this module.

The product is designed with form factor, optical/electrical connection and digital diagnostic interface according to the QSFP Multi-Source Agreement (MSA). It has been designed to meet the harshest external operating conditions including temperature, humidity and EMI interference. The module operates from a single +3.3V power supply and LVCMOS/LVTTL global control signals such as Module Present, Reset, Interrupt and Low Power Mode are available with the modules. A 2-wire serial interface is available to send and receive more complex control signals and to obtain digital diagnostic information. Individual channels can be addressed and unused channels can be shut down for maximum design flexibility.

The GQPLFG06D is designed with form factor, optical/electrical connection and digital diagnostic interface according to the QSFP Multi-Source Agreement (MSA). It has been designed to meet the harshest external operating conditions including temperature, humidity and EMI interference. The module offers very high functionality and feature integration, accessible via a two-wire serial interface.

● Absolute Maximum Ratings

| Parameter | Symbol | Min. | Typical | Max. | Unit |
|---------------------|--------------|------|---------|------|------|
| Storage Temperature | T_S | -40 | | +85 | °C |
| Supply Voltage | $V_{CC,T,R}$ | -0.5 | | 4 | V |
| Relative Humidity | RH | 0 | | 85 | % |

● Recommended Operating Environment:

| Parameter | Symbol | Min. | Typical | Max. | Unit |
|----------------------------|-------------|-------|---------|-------|------|
| Case operating Temperature | T_C | 0 | | +70 | °C |
| Supply Voltage | $V_{CCT,R}$ | +3.13 | 3.3 | +3.47 | V |
| Supply Current | I_{CC} | | | 1000 | mA |
| Power Dissipation | PD | | | 3.5 | W |

● Electrical Characteristics ($T_{OP} = 0$ to 70 °C, $V_{CC} = 3.13$ to 3.47 Volts)

| Parameter | Symbol | Min | Typ | Max | Unit | Note |
|--------------------------|----------|-----|---------|----------|------|------|
| Data Rate per Channel | | - | 10.3125 | 11.2 | Gbps | |
| Power Consumption | | - | 2.5 | 3.5 | W | |
| Supply Current | I_{CC} | | 0.75 | 1.0 | A | |
| Control I/O Voltage-High | V_{IH} | 2.0 | | V_{CC} | V | |
| Control I/O Voltage-Low | V_{IL} | 0 | | 0.7 | V | |
| Inter-Channel Skew | TSK | | | 150 | Ps | |
| RESETL Duration | | | 10 | | Us | |
| RESETL De-assert time | | | | 100 | ms | |
| Power On Time | | | | 100 | ms | |
| Transmitter | | | | | | |

| | | | | | | |
|---------------------------------------|-------|-----|-----|------|----|---|
| Single Ended Output Voltage Tolerance | | 0.3 | | 4 | V | 1 |
| Common mode Voltage Tolerance | | 15 | | | mV | |
| Transmit Input Diff Voltage | VI | 150 | | 1200 | mV | |
| Transmit Input Diff Impedance | ZIN | 85 | 100 | 115 | | |
| Data Dependent Input Jitter | DDJ | | | 0.2 | UI | |
| Data Input Total Jitter | TJ | | | 0.65 | UI | |
| Receiver | | | | | | |
| Single Ended Output Voltage Tolerance | | 0.3 | | 4 | V | |
| Rx Output Diff Voltage | Vo | 370 | 600 | 950 | mV | |
| Rx Output Rise and Fall Voltage | Tr/Tf | | | 35 | ps | 1 |
| Total Jitter | TJ | | | 0.2 | UI | |
| Deterministic Jitter | DJ | | | 0.65 | UI | |

Note:

1. 20~80%

● Optical Parameters(TOP = 0 to 70 °C, VCC = 3.0 to 3.6 Volts)

| Parameter | Symbol | Min | Typ | Max | Unit | Ref. |
|--|----------------|------------------------------------|-------|--------|-------|------|
| Transmitter | | | | | | |
| Wavelength Assignment | L0 | 1264.5 | 1271 | 1277.5 | nm | |
| | L1 | 1284.5 | 1291 | 1297.5 | nm | |
| | L2 | 1304.5 | 1311 | 1317.5 | nm | |
| | L3 | 1324.5 | 1331 | 1337.5 | nm | |
| Sidemode Suppression Ratio | SSRmin | 30 | | | dB | |
| Total Average Launch Power | P _T | | | 8.3 | dBm | |
| Transmit OMA per Lane | TxOMA | -6.0 | | 3.5 | dB | |
| Average Launch Power per Lane | TXPx | -10 | | 2.3 | dBm | |
| Average launch power of OFF transmitter, per lane | | | | -30 | dBm | |
| Optical Extinction Ratio | ER | 3.5 | | | dB | |
| Transmitter Eye Mask Definition {X1, X2, X3, Y1, Y2, Y3} | | {0.25, 0.4, 0.45, 0.25, 0.28, 0.4} | | | | |
| Relative Intensity Noise | Rin | | | -128 | dB/HZ | 1 |
| Optical Return Loss Tolerance | | | | 12 | dB | |
| Receiver | | | | | | |
| Damage Threshold | THd | 3.5 | | | dBm | 1 |
| Receiver Sensitivity, each Lane | R | | -11.5 | | dBm | |

| | | | | | | |
|--|------------------|-------|--|-------|-----|--|
| Receive Power (OMA) per Lane | RxOMA | | | 3.5 | dB | |
| Average Receive Power per Lane | RXPx | -13.7 | | 2.3 | | |
| Receiver Sensitivity (OMA) per Lane | Rxsens | | | -10.5 | | |
| Receive Electrical 3 dB upper Cut off Frequency, each Lane | | | | 12.3 | GHz | |
| RSSI Accuracy | | -2 | | 2 | dB | |
| Receiver Reflectance | Rrx | | | -12 | dB | |
| LOS De-Assert | LOS _D | | | -13 | dBm | |
| LOS Assert | LOS _A | -30 | | | dBm | |
| LOS Hysteresis | LOS _H | 0.5 | | | dB | |

Note

1. 12dB Reflection


● Diagnostic Monitoring Interface

Digital diagnostics monitoring function is available on all QSFP+ IR4. A 2-wire serial interface provides user to contact with module. The structure of the memory is shown in flowing. The memory space is arranged into a lower, single page, address space of 128 bytes and multiple upper address space pages. This structure permits timely access to addresses in the lower page, such as Interrupt Flags and Monitors. Less time critical time entries, such as serial ID information and threshold settings, are available with the Page Select function. The interface address used is A0xh and is mainly used for time critical data like interrupt handling in order to enable a one-time-read for all data related to an interrupt situation. After an interrupt, IntL has been asserted, the host can read out the flag field to determine the affected channel and type of flag.

| Byte Address | Description | Type |
|--------------|------------------------------------|------------|
| 0 | Identifier (1 Byte) | Read Only |
| 1-2 | Status (2 Bytes) | Read Only |
| 3-21 | Interrupt Flags (31 Bytes) | Read Only |
| 22-33 | Module Monitors (12 Bytes) | Read Only |
| 34-81 | Channel Monitors (48 Bytes) | Read Only |
| 82-85 | Reserved (4 Bytes) | Read Only |
| 86-97 | Control (12 Bytes) | Read/Write |
| 98-99 | Reserved (2 Bytes) | Read/Write |
| 100-106 | Module and Channel Masks (7 Bytes) | Read/Write |
| 107-118 | Reserved (12 Bytes) | Read/Write |
| 119-122 | Reserved (4 Bytes) | Read/Write |
| 123-126 | Reserved (4 Bytes) | Read/Write |
| 127 | Page Select Byte | Read/Write |

| Byte Address | Description | Type |
|--------------|------------------------------|------------|
| 128-175 | Module Thresholds (48 Bytes) | Read Only |
| 176-223 | Reserved (48 Bytes) | Read Only |
| 224-225 | Reserved (2 Bytes) | Read Only |
| 226-239 | Reserved (14 Bytes) | Read/Write |
| 240-241 | Channel Controls (2 Bytes) | Read/Write |
| 242-253 | Reserved (12 Bytes) | Read/Write |
| 254-255 | Reserved (2 Bytes) | Read/Write |

2-wire serial address, 1010000x (A0h)"



| Address | Name | Description |
|---------|---|--|
| 128 | Identifier (1 Byte) | Identifier Type of serial transceiver |
| 129 | Ext. Identifier (1 Byte) | Extended identifier of serial transceiver |
| 130 | Connector (1 Byte) | Code for connector type |
| 131-138 | Transceiver (8 Bytes) | Code for electronic compatibility or optical compatibility |
| 139 | Encoding (1 Byte) | Code for serial encoding algorithm |
| 140 | BR, nominal (1 Byte) | Nominal bit rate, units of 100 Mb/s |
| 141 | Extended RateSelect Compliance (1 Byte) | Tags for Extended RateSelect compliance |
| 142 | Length SMF (1 Byte) | Link length supported for SM fiber in km |
| 143 | Length E-50 μ m (1 Byte) | Link length supported for EBW 50/125 μ m fiber, units of 2 m |
| 144 | Length 50 μ m (1 Byte) | Link length supported for 50/125 μ m fiber, units of 1 m |
| 145 | Length 62.5 μ m (1 Byte) | Link length supported for 62.5/125 μ m fiber, units of 1 m |
| 146 | Length copper (1 Byte) | Link length supported for copper, units of 1 m |
| 147 | Device Tech (1 Byte) | Device technology |
| 148-163 | Vendor name (16 Bytes) | QSFP vendor name (ASCII) |
| 164 | Extended Transceiver (1 Byte) | Extended Transceiver Codes for InfiniBand [†] |
| 165-167 | Vendor OUI (3 Bytes) | QSFP vendor IEEE vendor company ID |
| 168-183 | Vendor PN (16 Bytes) | Part number provided by QSFP vendor (ASCII) |
| 184-185 | Vendor rev (2 Bytes) | Revision level for part number provided by vendor (ASCII) |
| 186-187 | Wavelength (2 Bytes) | Nominal laser wavelength (Wavelength = value / 20 in nm) |
| 188-189 | Wavelength Tolerance (2 Bytes) | Guaranteed range of laser wavelength (+/- value) from Nominal wavelength (Wavelength Tol. = value / 200 in nm) |
| 190 | Max Case Temp (1 Byte) | Maximum Case Temperature in Degrees C |
| 191 | CC_BASE (1 Byte) | Check code for Base ID fields (addresses 128-190) |
| 192-195 | Options (4 Bytes) | Rate Select, TX Disable, TX Fault, LOS |
| 196-211 | Vendor SN (16 Bytes) | Serial number provided by vendor (ASCII) |
| 212-219 | Date code (8 Bytes) | Vendor's manufacturing date code |
| 220 | Diagnostic Monitoring Type (1 Byte) | Indicates which type of diagnostic monitoring is implemented |
| 221 | Enhanced Options (1 Byte) | Indicates which optional enhanced features are implemented |
| 222 | Reserved (1 Byte) | Reserved |
| 223 | CC_EXT | Check code for the Extended ID Fields (addresses 192-222) |
| 224-255 | Vendor Specific (32 Bytes) | Vendor Specific EEPROM |

Page02 is User EEPROM and its format decided by user.

The detail description of low memory and page00.page03 upper memory please see SFF-8436 document.

● Timing for Soft Control and Status Functions

| Parameter | Symbol | Max | Unit | Conditions |
|--------------------------------|--------------|------|------|--|
| Initialization Time | t_init | 2000 | ms | Time from power on1, hot plug or rising edge of Reset until the module is fully functional2 |
| Reset Init Assert Time | t_reset_init | 2 | μs | A Reset is generated by a low level longer than the minimum reset pulse time present on the ResetL pin. |
| Serial Bus Hardware Ready Time | t_serial | 2000 | ms | Time from power on1 until module responds to data transmission over the 2-wire serial bus |
| Monitor Data Ready Time | t_data | 2000 | ms | Time from power on1 to data not ready, bit 0 of Byte 2, deasserted and IntL asserted |
| Reset Assert Time | t_reset | 2000 | ms | Time from rising edge on the ResetL pin until the module is fully functional2 |
| LPMODE Assert Time | ton_LPMODE | 100 | μs | Time from assertion of LPMODE (Vin:LPMODE =Vih) until module power consumption enters lower Power Level |
| IntL Assert Time | ton_IntL | 200 | ms | Time from occurrence of condition triggering IntL until Vout:IntL = Vol |
| IntL Deassert Time | toff_IntL | 500 | μs | toff_IntL 500 μs Time from clear on read3 operation of associated flag until Vout:IntL = Voh. This includes deassert times for Rx LOS, Tx Fault and other flag bits. |
| Rx LOS Assert Time | ton_los | 100 | ms | Time from Rx LOS state to Rx LOS bit set and IntL asserted |
| Flag Assert Time | ton_flag | 200 | ms | Time from occurrence of condition triggering flag to associated flag bit set and IntL asserted |
| Mask Assert Time | ton_mask | 100 | ms | Time from mask bit set4 until associated IntL assertion is inhibited |
| Mask De-assert Time | toff_mask | 100 | ms | Time from mask bit cleared4 until associated IntL operation resumes |
| ModSelL Assert Time | ton_ModSelL | 100 | μs | Time from assertion of ModSelL until module responds to data transmission over the 2-wire serial bus |
| ModSelL Deassert Time | toff_ModSelL | 100 | μs | Time from deassertion of ModSelL until the module does not respond to data transmission over the 2-wire serial bus |
| Power_over-ride or | ton_Pdown | 100 | ms | Time from P_Down bit set 4 until module |

| | | | | | |
|-----------------------------------|-----------|------------|-----|----|---|
| Power-set Time | Assert | | | | power consumption enters lower Power Level |
| Power_over-ride or Power-set Time | De-assert | toff_Pdown | 300 | ms | Time from P_Down bit cleared ⁴ until the module is fully functional ³ |

Note:

1. Power on is defined as the instant when supply voltages reach and remain at or above the minimum specified value.
2. Fully functional is defined as IntL asserted due to data not ready bit, bit 0 byte 2 de-asserted.
3. Measured from falling clock edge after stop bit of read transaction.
4. Measured from falling clock edge after stop bit of write transaction.

● Transceiver Block Diagram




Figure 1: 40Gb/s QSFP IR4 Transceiver Block Diagram

● Pin Assignment




Diagram of Host Board Connector Block Pin Numbers and Name

● Pin Description


| Pin | Logic | Symbol | Name/Description | Ref. |
|-----|-------------|---------|--------------------------------------|------|
| 1 | | GND | Ground | 1 |
| 2 | CML-I | Tx2n | Transmitter Inverted Data Input | |
| 3 | CML-I | Tx2p | Transmitter Non-Inverted Data output | |
| 4 | | GND | Ground | 1 |
| 5 | CML-I | Tx4n | Transmitter Inverted Data Output | |
| 6 | CML-I | Tx4p | Transmitter Non-Inverted Data Output | |
| 7 | | GND | Ground | 1 |
| 8 | LVTTL-I | ModSelL | Module Select | |
| 9 | LVTTL-I | ResetL | Module Reset | |
| 10 | | VccRx | +3.3V Power Supply Receiver | 2 |
| 11 | LVC MOS-I/O | SCL | 2-Wire Serial Interface Clock | |
| 12 | LVC MOS-I/O | SDA | 2-Wire Serial Interface Data | |
| 13 | | GND | Ground | 1 |
| 14 | CML-O | Rx3p | Receiver Inverted Data Output | |
| 15 | CML-O | Rx3n | Receiver Non-Inverted Data Output | |
| 16 | | GND | Ground | 1 |
| 17 | CML-O | Rx1p | Receiver Inverted Data Output | |
| 18 | CML-O | Rx1n | Receiver Non-Inverted Data Output | |
| 19 | | GND | Ground | 1 |
| 20 | | GND | Ground | 1 |
| 21 | CML-O | Rx2n | Receiver Inverted Data Output | |
| 22 | CML-O | Rx2p | Receiver Non-Inverted Data Output | |
| 23 | | GND | Ground | 1 |
| 24 | CML-O | Rx4n | Receiver Inverted Data Output | |
| 25 | CML-O | Rx4p | Receiver Non-Inverted Data Output | |
| 26 | | GND | Ground | 1 |
| 27 | LVTTL-O | ModPrsL | Module Present | |
| 28 | LVTTL-O | IntL | Interrupt | |
| 29 | | VccTx | +3.3V Power Supply Transmitter | 2 |
| 30 | | Vcc1 | +3.3V Power Supply | 2 |
| 31 | LVTTL-I | LPMODE | Low Power Mode | |
| 32 | | GND | Ground | 1 |
| 33 | CML-I | Tx3p | Transmitter Inverted Data Output | |
| 34 | CML-I | Tx3n | Transmitter Non-Inverted Data Output | |

| | | | | |
|----|-------|------|--------------------------------------|---|
| 35 | | GND | Ground | 1 |
| 36 | CML-I | Tx1p | Transmitter Inverted Data Output | |
| 37 | CML-I | Tx1n | Transmitter Non-Inverted Data Output | |
| 38 | | GND | Ground | 1 |


Notes:

1. GND is the symbol for single and supply(power) common for QSFP modules, All are common within the QSFP module and all module voltages are referenced to this potential otherwise noted. Connect these directly to the host board signal common ground plane. Laser output disabled on TDIS >2.0V or open, enabled on TDIS <0.8V.
2. VccRx, Vcc1 and VccTx are the receiver and transmitter power suppliers and shall be applied concurrently. Recommended host board power supply filtering is shown below. VccRx, Vcc1 and VccTx may be internally connected within the QSFP transceiver module in any combination. The connector pins are each rated for maximum current of 500mA.

● Recommended Circuit



● Mechanical Dimensions



TIBTRONIX reserves the right to make changes to the products or information contained herein without notice. No liability is assumed as a result of their use or application. No rights under any patent accompany the sale of any such products or information.

Published by Shenzhen TIBTRONIX Technology Co., Ltd.

Copyright © TIBTRONIX

All Rights Reserved.