

5 IN 1 CABLE TESTER



Description

1. LCD screen display
2. RJ11, RJ45, BNC port
3. Open, short, jump, reverse, cross talk test
4. Check, sequence, locator

Feature

1. Large LCD screen, digital and tone display
2. Hunt cat3, 5E, 6E, coaxial cable and wire
3. Check open, short, jump, reverse or cross-talk
4. Wire sort and circuit status test
5. Locate the wiring or connection error
6. Measure cable length, determine the distance of open & short
7. Self-checking function and automatically compensate any change
8. Far-end recognizer with prompting voice

Specifications

Test range	m	1~350 (3~1200 feet)
Accuracy		3% (+/-0.5M or +/-1.5 ft)(calibrating cable > 5M) 5% (+/-0.5M or +/-1.5 ft).(AMP, AT&T Class 5 cable)
Display Unit		Meter or feet
Display		4*16 character big screen LCD (61.6* 25.2mm)
Port		RJ11, RJ45, BNC
Test Cable		UTP, STP network cable, coaxial cable, telephone line
Detect Cable		UTP, STP network cable, coaxial cable, telephone line, wire
Auto power-off	min	30
Power supply	V	9 (receiver), 6 (main tester)
Operation Temperature	C	-10 ~ 60
Dimension	mm	180*80*40 main tester 218*46*29 receiver 77*31*21 remote identifier